

# INSTRUCTIONS FOR:

**9905 - 9-16 1/8 INCH (230-425mm) ADJUSTABLE SPEED RING**

**9915 – 12-21½ INCH (305-545mm) ADJUSTABLE SPEED RING**

**9925 – 18½-31 INCH (470-787mm) ADJUSTABLE SPEED RING**

This Adjustable Speed Ring has been designed to fit a wide range of lighting fixtures. Measure the distance between the barn door ears of your light. Set the four adjustable sliders on the ring to that measurement. Lock each down with the thumbscrew. Attach to your light by sliding the Ring into the barn door ears much like the standard circular rings.

When shooting, keep the top rear flap and the top and bottom vents of the Lightbank open to ensure proper ventilation.

This Speed Ring fits both Daylite and Quartz Lightbanks. Quartz Lightbanks work with the 11/32" (9mm) hole marked "Q". Daylite Lightbanks work with the 1/2" (13mm) hole marked "D". When using this ring with older small and medium Daylite Banks, it is preferable to use the new larger diameter Daylite poles, #4032 and #4037.

The 9905 Speed Ring will fit lights with the barn door ears at either the 90-degree or the 45-degree positions. The 9915 and 9925 Speed Rings will fit lights with the barn door ears in the 90-degree position only. The 9915 and 9925 Speed Rings will not fit LTM lights.

## Parts list: 9905

1 – 99051000 17.5" ring  
2 – 99052000 left slider bracket  
2 – 99053000 right slider bracket  
4 – 99055000 3/8-16 x 1 ¼" steel t-screw  
4 – 99058000 nylon washer

## Parts list: 9915

1 – 99151000 21.5" ring  
2 – 99152000 left slider bracket  
2 – 99153000 right slider bracket  
4 – 99055000 3/8-16 x 1 ¼" steel t-screw  
4 – 99058000 nylon washer

## Parts list: 9925

1 – 99251000 30" ring  
2 – 99252000 left slider bracket  
2 – 99253000 right slider bracket  
4 – 99055000 3/8-16 x 1 ¼" steel t-screw  
4 – 99058000 nylon washer